

# CUSTOMER APPLICATION MEMO

CUSTOMER:  
DATE: 2003

\*

ISSUE

BY: EEF

PREPARED

MODEL:

BH 2000 VIP – C6  
Rev #02 (06--08)

See Last Page

MACHINE NO.:

## POWER REQUIREMENTS

- \* (1) 208 Volt - 30 AMP, 5 Wire w/neutral, Three Phase, 50/60 HZ Main Power Line
- \* (1) 120 Volt - 30 AMP, 3 Wire, Single Phase, 50/60 HZ Modular Delivery Power Line

## FRAMING

Shuttle Feed Hopper w/HCEL  
Turnover  
Envelope Marker  
Diverter

- \* Telescoping Interface
- \* (1) Hasler WJ PRO Meter Base and Light Post with Modular Stand  
60" Standard End Conveyor

## ATTACHMENTS

1. Open Feed Station with front/rear GBR 438 mounting interface required.
2. Packaged “VIP” (GBR 438) Cut Sheet Feeder with one top and one bottom mounted standard OMR probes, also one top mounted BCR Head required.
3. Due to the extended length of the HCEL on a six station machine an additional 21” section must be added.

## SUPPLEMENTARY INFORMATION

- \* 1. This machine to be equipped with the Multiple Weight Metering and Computer Weighing system functions.

**\*\*End of Machine Specifications\*\***

**Top of Form**

**OMR MARK PATTERN TO BE READ**

<b>OMR Mark Bank "A"</b>	<b>System Function</b>	<b>Location</b>
1 <sup>st</sup> Mark	Gate/Read Verify	Every Page
2 <sup>nd</sup> Mark	Demand Feed	Every Page Except Last Page Fed
3 <sup>rd</sup> Mark	Select #1	Last Page
4 <sup>th</sup> Mark	Select #2	Last Page
5 <sup>th</sup> Mark	Zip Mark	Last Page
6 <sup>th</sup> Mark	Customer ID 1	Every Page
7 <sup>th</sup> Mark	Customer ID 2	Every Page
8 <sup>th</sup> Mark	Customer ID 4	Every Page
9 <sup>th</sup> Mark	Divert	Last Page
10 <sup>th</sup> Mark	Select #3	Last Page
11 <sup>th</sup> Mark	Select #4	Last Page
12 <sup>th</sup> Mark	Select #5	Last Page
13 <sup>th</sup> Mark	Select #6	Last Page
14 <sup>th</sup> Mark	Unused	Not Used
15 <sup>th</sup> Mark	Unused	Not Used
16 <sup>th</sup> Mark	Unused	Not Used
17 <sup>th</sup> Mark	Unused	Not Used

**Top of Form**

**FUTURE 3of9 BARCODE TO BE READ**

	<b>System Function</b>	<b>Location</b>
Start Character		
Character 1 - Bit 5	Demand Feed	Every Page except Last Page
Bit 4	Select #1	Last Page
Bit 3	Select #2	Last Page
Bit 2	Zip Mark	Last Page
Bit 1	Customer ID 1	Every Page
Character 2 – Bit 5	Customer ID 2	Every Page
Bit 4	Customer ID 4	Every Page
Bit 3	Divert	Last Page
Bit 2	Select #3	Last Page
Bit 1	Select #4	Last Page
Character 3 – Bit 5	Select #5	Last Page
Bit 4	Select #6	Last Page
Bit 3	Spare	Not Used
Bit 2	Spare	Not Used
Bit 1	Spare	Not Used
Stop Char.		

